



The inDESIGN MP60D – 60 watt, all-in-one mixer amplifier is designed for small to medium installations where multiple playback sources are required. The in-built FM tuner, DAB+ tuner, USB/MP3 player and BT player allow easy playback of your favourite radio station, or music stored on an array of devices.

The MP60D delivers 60 watts via 8Ω or constant voltage 100V and 70V speaker outputs and features 2 Microphone/Line inputs with individual gain control for external audio sources and microphones. A 'pre-amp out/power amp in' link allows for the mixer audio signal to be sent to an external equaliser or a booster amplifier.

MODEL	MP60D
Output power	60 watts. 8Ω or constant voltage 100v/70v line
AC power supply	Internal universal power supply (110VAC - 240VAC)
Output low impedance	8 ohm
Hi impedance output	70V / 83 ohm 100V / 166 ohm
Input sensitivity	Microphone 5mV Line 500mV
Frequency response	90Hz – 16KHz, +/- 1dB
THD (at -3dB rate power)	-0.5% @ 1KHz
Tone control	Bass 100Hz + - 10dB, Treble 10kHz + - 10dB
Protection	Thermal protected (at 75 degrees), short circuit overload
Size mm.	220 x 66 x 200
Weight kg (Net)	3.5
FM radio	88 – 108MHz. 10 preset stations
DAB+ frequency range	168MHz – 240MHz
Bluetooth	V3.0, V4.0 supported
USB playback	MP3 & WMA supported
Line Output level	600mV
Mains power	Internal universal power supply (110VAC - 240VAC)
Power consumption	100 watts
Safety	RCM / CE / EMC
Channel separation	>50dB
Noise level	<75dB
DC power supply	21-25V
AC fuse	T1AH 250V 5 x 20 mm

Description and specifications are correct at time of printing. May be subject to change without notice.