

MA4200

ORDER CODE: PA-MA4200

2.1 CHANNEL MULTIMEDIA MIXER AMPLIFIER



Features

- High powered, efficient Class D audio amplifiers built in.
- Compact all-in-one design in a professional 1RU 19" metal chassis.
- No noisy cooling fans.
- Bass, treble and balance control.
- L&R and SUBWOOFER volume controls.
- Low-pass control (50-150Hz) and tone control for subwoofer.
- TWO AUX inputs with individual volume control (1 x RCA stereo and 1 x Phone jack 3,5mm stereo).
- MIC IN (XLR or Phone jack 6,3mm).
- AUX OUT (RCA stereo connector, line level).
- Assistive listening device (ALD) output (Phone jack 3.5mm) with volume control.
- DC power output 12V/200mA x 1, 5VDC output (USB A) for supplying low power accessories x 1.
- VOICE PRIORITY & LOW CUT (switchable) for all MIC inputs.
- Inputs matched for smart-phone audio outputs.
- Easy-to-use design, no technical background needed.
- Plug and play without special connectors or tools, USER-friendly!
- Available optional modules: RX8D, RX8TD, DPR5, BT5.

Specifications

Model	MA4200
Supply voltage	18~24VDC / 5A min. (by external switching power supply)
Power output	All in all about 200W RMS
Frequency response	L&R: 20~20,000Hz±3dB Subwoofer: 20~250Hz±3dB
Input wired microphone	1 x XLR phantom powered 1 x Phone jack 6.3mm
All microphone inputs	Voice priority and low cut switch on front panel
Input AUX 1	RCA (stereo) line level
Input AUX 2	Phone jack 3.5mm (stereo) line level
Output AUX	RCA (stereo) line level (output of mixed signal)
Outputs L&R	Phone jack 6.3mm (mono) & screw terminals 5.08mm
Output subwoofer	Phone jack 6.3mm (mono) & screw terminals 5.08mm 0°/180° phase switch provided on the rear side
Output ALD	Phone jack 3.5mm (stereo) line level
Output USB	Socket type A, for external low power devices (200mA max.)
Output DC	About 12VDC/200mA for external low power devices
Dimensions (mm)	482 (W) x 200 (D) x 44 (H)
Weight (kg)	2.06

* **NOTE:** The above specifications are subject to change without prior notice.