



## Portable Radio Frequency Receiver 865MHz / 915MHz

RF-RX1-865 / RF-RX1-915

A lightweight Portable Radio Frequency Receiver which provides high-quality sound received from compatible transmitters, with two versions that respectively work on 865MHz (UK/EU) or 915MHz (USA/AU) frequencies.

There is no limit to the number of receivers which can be used per group. The receiver utilises digital audio transmission technology. A micro-USB power supply provides fast and simple charging and the unit can also be charged using the drop-in RF-DC6/RF-DC24 charging trays.

### Physical Data

Dimensions	Height – 88mm (3.46") Width – 64mm (2.51") Depth – 29mm (1.14") [without antenna]
Weight	109.5g (0.24lbs)
Construction	Mixed

### Technical Data

Emission Modulation	4GFSK
Antenna	Flexible antenna
Headphone Output	3.5mm
Line Output	3.5mm
Batteries	2 x AA 1.2V 2100mA rechargeable (NiMH)
Battery Life	>10 hours
Frequency Response	70Hz – 12kHz
Channel	42 simultaneous groups
Display	White Backlit LCM
Selectable Features	Auto-On / Auto-Lock
Software	Smart programming software [OKAY-CON-SW] for fast setup of multiple receivers

### Applications

Ideal for assistive listening, tour guidance, or interpretation.

- Museums
- Historical Sites
- Exhibitions/Events/Conferences
- Outdoor Tours
- Assistive Listening

### What's in the Box

- Portable Radio Frequency Receiver [RF-RX1-865/915]
- Lanyard [RF-LAN]
- Micro-USB Power Cable [USB-M100]
- Earphones [RF-IEH]
- 2 x AA 1.2V 2100mA rechargeable (NiMH) batteries [only included with 865MHz, not in 915MHz]

### Compatible Accessories

- Portable Radio Frequency Transmitter [RF-TX1-865/915]
- Stationary Radio Frequency Transmitter [RF-TXRM-865/915]
- Portable Radio Frequency Handheld Transmitter [RF-TXHH-865/915]
- 6/24 Bay Charger Tray [RF-DC6/RF-DC24]
- Inductive Neck Loop [RF-NL1]
- Headphones [RF-HPI]

Talk to us now:

+44 (0) 1732 223900 (UK & ROW)

+1 616 392 3400 (US & Canada)

[www.contacta.co.uk](http://www.contacta.co.uk)

