Compact P.A Amplifier

PA-1000B





INTERM PA-1000B PUBLIC ADDRESS AMPLIFIER



OVERVIEW

The PA-1000B is a 30W public address mixer/amplifier with two balanced low-impedance (or unbalanced high impedance) mic inputs, allowing connections of two dynamic microphones. Input three is for connection of any line level source. The unit also features an input from a 600Ω (0,775V) telephone system paging port. Muting is accomplished via voice activation from Mic1, or telephone input for paging. The PA-1000B has bass and treble controls. A four-tone chime is usable for page pre-announcement.

FEATURES

VERSATILE AND CONVENIENT

Two Mic input channels with both XLR and phone jack, and an Aux input channel.

ANNOUNCEMENT CHIME Convenient four-tone chime for use with announcements, Can be operated remotely.

PRIORITY MUTING

Mic1 input and chime mute other inputs when in use. Mute level is adjustable via rear panel control,

DIGITAL TUNER

Easy-to-use, fully digital AM/FM tuner with 30 memory locations for storing your favorite stations.










Restaurant and Cafe

Classroom


Lobby

Theme Park












			PA-1000B
Rated Output Power			30W (RMS)
Frequency Response			120Hz-15kHz
T.H.D (at 1kHz Rated Output)			Less than 1%
Tone Control (100Hz, 10kHz)			±10dB
Input Sensitivity/ Impedance	Mic 1 and 2		$1mV/10k\Omega$, Balanced Phone, $0.3mV/600\Omega$, Balanced XLR
	Aux In		0.775V/10kΩ
	Tel In	EC & Associated	0.775\/600Ω
		USA/CANADA & Associated	0.3V/600Ω
	Amp In		1V/10kΩ
Line Out/Impedance			1V/600Ω
Music On Hold/Impedance			0.775V/600Ω
Operating Temperature			$-10^{\circ}\text{C} \sim +40^{\circ}\text{C}$
Power Source			100 – 120VAC or 220 – 240VAC; 50/60Hz (Supplied AC mains transformer depends on country requirements)
Power Consumption			45W
Weight			4.6kg/10lb
Dimensions (W x H x D)			300 x 88 x 260mm/11.8 x 3.5 x 10.2in





719, Dobong-ro, Dobong-gu, Seoul, Korea Overseas Sales Team Tel_ +82-2-2289-8141~7 Fax_ +82-2-2289-8149 E-mail_ overseas@inter-m.com

www.inter-m.com